

# DYNA

# INDUSTRIAL

	DP3000	DP5000	DP7500	W3000H	W6000HE	W10000VE	WL12000HE/C	WL12000HE/B	WL16000VE	WL18000VE	WL22000VE/A	WL22000VE/C	W6010DE
<b>ELECTRICAL DATA</b>													
Starting Watts	3,000	5,000	7,500	3,000	6,000	10,000	12,000	12,000	16,000	18,000	22,000	22,000	6,010
Running Watts	2,500	4,560	6,720	2,400	5,500	9,600	10,800	10,800	14,000	16,500	19,000	19,000	5,000
Output (V)	120	120/240	120/240	120	120/240	120/240	120/240	120/240	120/240	120/240	120/240	120/240	120/240
Running Amps	20.8	38/19	56/28	20	45.8/22.9	80/40	90/45	90/45	116/58	137.5/68.75	158/79	158/79	40/20
Voltage Regulation	Capacitor +/-5%	Capacitor +/-5%	Capacitor +/-5%	Capacitor +/-5%	AVR +/-1%	AVR +/-1%	Capacitor +/-5%	Capacitor +/-5%	Capacitor +/-5%	Capacitor +/-5%	AVR +/-1.5%	AVR +/-1.5%	Capacitor +/-5%
Motor Starting <sup>(1)</sup>	1 hp	1.5 hp	2 hp	0.75 hp	1.5 hp	3 hp	3.5 hp	3.5 hp	4 hp	5 hp	6 hp	6 hp	1.5 hp
<b>ENGINE DATA</b>													
Make	Honda	Honda	Honda	Honda	Honda	B&S	Honda	Honda	Honda	B&S	B&S	B&S	Kohler
Model	GX160	GX270	GX390	GC160	GX340	Vanguard	GX630	GX630	iGX800	Vanguard	Vanguard	Vanguard	KD440
Fuel Type	Gasoline	Gasoline	Gasoline	Gasoline	Gasoline	Gasoline	Gasoline	Gasoline	Gasoline	Gasoline	Gasoline	Gasoline	Diesel
Starting System <sup>(2)</sup>	Recoil Only	Recoil Only	Rec/Elec	Recoil Only	Electric	Rec/Elec	Electric	Electric	Electric	Electric	Electric	Electric	Electric
CARB	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No	No	No	No
DBA @ 7 Meters	74	80.6	83.7	72	84	82.8	77	77	82	78	79	79	87.6
<b>FUEL</b>													
Fuel Tank	1 gal	8 gal	8 gal	2 qt	7 gal	7 gal	15 gal	15 gal	15 gal	15 gal	15 gal	15 gal	7 gal
Fuel Consumption (full load)	0.45 gal/hr	0.75 gal/hr	1.0 gal/hr	1.3 qt/hr (half load)	0.87 gal/hr	1.6 gal/hr	1.6 gal/hr	1.6 gal/hr	2.1 gal/hr	2.5 gal/hr	3.28 gal/hr	3.28 gal/hr	0.50 gal/hr
<b>RECEPTACLES</b>													
120 Volt Receptacles	5-20 GFCI	(2) 5-20 GFCI	(2) 5-20 GFCI	5-20 GFCI	(2) 5-20 GFCI	(2) 5-20 GFCI	(3) 5-20 GFCI	(3) 5-20 GFCI	(3) 5-20 GFCI	(2) 5-20 GFCI L5-20 GFCI	(2) 5-20 GFCI	(2) 5-20 GFCI	(2) 5-20 GFCI L5-30 GFCI
120/240 Volt Receptacles	N/A	L14-30 GFCI	L14-30 GFCI	N/A	L14-30 GFCI	14-50 GFCI	CS6369 50A	14-60	CS6369 50A	14-60 L14-30 GFCI	(2) 14-50 GFCI	CS6369 50A L14-30 GFCI	L14-30 GFCI
240 Volt Receptacles	N/A	N/A	N/A	N/A	N/A	L6-30 GFCI	L6-30 GFCI	L6-30 GFCI	(2) L6-30 GFCI	L6-30 GFCI	L6-30 GFCI	ANDERSON	N/A

Notes: (1) Code G capacitor start motor. (2) Electric start models include battery rack and cables. Battery not included



## OPTIONAL ACCESSORIES

### DOLLY KITS

- Two-Wheel - 5-10kW
- Four-Wheel - 12-22kW

### EMERGENCY TRANSFER SWITCH

- Outdoor enclosure
- Premium circuit breaker load center

### MAINTENANCE KIT

- Premium synthetic 5W-30 oil
- Sta-bil fuel stabilizer
- Spark plug
- Air filter

### GENERATOR COVER

- Made of heavy canvas
- Weather resistant

### PLUGS

- L14-30 30 A
- 14-60 60A
- CS6365 50A
- 14-50 50A
- Anderson Plug
- 30A 20ft cord set

### BATTERY

- Interstate 300 CCA

### BATTERY CHARGER

- Smart 3 stage 1.5 Amps trickle charger



GENERATOR EXPERTS

# WINCO<sup>®</sup> GENERATORS

An American Company.

We produce our products in our 200,000ft<sup>2</sup> facility located in Le Center, Minnesota, equipped with modern engineering, fabrication and assembly capabilities.



## Why WINCO

WINCO is known for portable generators, especially the "Big Dog" industrial generators that have been the gold standard for large air-cooled power for almost two decades! Commercial engines and a rugged design make our generators dependable, durable, and just plain awesome.

Distributed By:

[www.wincogen.com](http://www.wincogen.com)

225 S. Cordova Ave • Le Center, MN 56057 • 1-800-733-2112

L-1001/E

# WINCO GENERATORS

An American Company



## INDUSTRIAL PORTABLE & VEHICLE MOUNTED GENERATORS

## EMERGEN-C

EC6010DR EC18000VE EC22000VE

### ELECTRICAL DATA

Starting Watts	6,010	18,000	22,000
Running Watts	5,000	15,000	19,000
Output (V)	120/240	120/240	120/240 1-PH 120/208 3-PH 120/240 3-PH 277/480 3-PH
Running Amps	40/20	125/62.5	158/79 1-PH
Voltage Regulation	AVR +/-1%	Capacitor +/-5%	AVR +/-1.5%
Motor Starting <sup>(1)</sup>	2 HP	5 hp	6 hp

### ENGINE DATA

Make	Kohler	B&S	B&S
Model	KD440	Vanguard	Vanguard
Fuel Type	Diesel	Gasoline	Gasoline
Low Oil Protection	Standard	Standard	Standard
Starting System <sup>(2)</sup>	Electric	Electric	Electric
CARB	No	No	No
DBA @ 7 Meters	87.6	79	79

### FUEL

Fuel Tank	N/A	Optional	Optional
Fuel Consumption <sup>(3)</sup>	0.50 gal/hr	2.69 gal/hr	3.28 gal/hr

### RECEPTACLES

Meter	YourGen	Hour Meter	Hour Meter
120/240V Receptacles	L14-30 30A	14-60 60A	Hard Wired

Notes: (1) Code G capacitor start motor. (2) Electric start models include battery rack and cables. Battery not included (3) Fuel consumption is estimated at full load.

