

400 Watts Portable AC Power with 250 PSI Air Compressor



Provides Portable Power, Vehicle Jump Start and a Built-in Air Compressor

Powered by a rechargeable battery, XPower Powerpack 400 Plus provides up to 400 watts of AC power. It can jump start a car, truck, boat or small RV and includes a built-in air compressor for inflating tires, small sport and camping equipment and more. The system also operates a wide range of DC products. Ideal for power emergencies, XPower Powerpack 400 Plus comes with a built-in emergency light and jumper cables.

Product Features

- ▶ Runs 115-volt AC or 12-volt DC products anywhere
- ▶ Built-in 400 watt inverter
- ▶ Sealed, non-spillable 20 amp-hour AGM battery
- ▶ 250 PSI Air compressor for inflating tires and small sports equipment
- ▶ Jumper cables designed for safe and efficient jump-starting
- ▶ Built-in light provides illumination in emergency situations at home and on the road
- ▶ 3-digit display allows for easy battery status monitoring
- ▶ Audible alarm signals overheat and under voltage conditions
- ▶ Overload and over-temperature protection to ensure longer inverter life
- ▶ AC charger stored in the unit
- ▶ Recharge at home or from a vehicle

Accessories

- ▶ Jumper Cables - use XPower Powerpack 400 Plus to jump-start your vehicle
- ▶ Nozzle Adapters - pump air into your vehicle tires or small inflatable sports equipment
- ▶ AC Charger - recharge XPower Powerpack 400 Plus from a standard wall outlet
- ▶ DC Charging Cable - recharge XPower Powerpack 400 Plus from your car, truck, boat or RV
- ▶ Accessory bag

Applications

For Outdoor and Indoor Applications:

- ▶ Pumps air into small inflatable sports equipment
- ▶ Powers camcorders, video games, stereos, 13" TV/VCR combos
- ▶ Runs hand-held blenders, fans, computers, laptops, clock radios, small power tools

For Emergency Situations:

- ▶ Inflates tires
- ▶ Jump-starts vehicles
- ▶ Charges cordless and cellular phones
- ▶ Powers emergency light, TVs and radios



Xantrex Technology Inc.

Headquarters
8999 Nelson Way
Burnaby, British Columbia
Canada V5A 4B5
800 670 0707 Toll Free
604 420 1591 Fax

5916 195th Street NE
Arlington, Washington
USA 98223
800 446 6180 Toll Free
360 925 5144 Fax

www.xantrex.com

400 Watts Portable AC Power with 250 PSI Air Compressor

Electrical Specifications

115 volt AC section		12 volt DC section	
AC output power (max. continuous)	320 W	Internal battery type	Sealed lead acid, AGM
AC output power (5 minutes)	400 W	Internal battery capacity	20 amp-hours, 200 CCA
AC surge power (peak)	640 W	Internal battery voltage	12 VDC (nominal)
AC output voltage (nominal)	115 V	DC power socket (circuit breaker)	12 amps (automatic reset)
AC output frequency	60 Hz +/-4 Hz		
AC output waveform	Modified sine wave		
Inverter no-load current	< 0.20 amps (battery drain with no load on inverter)		
Charging system		Charging time	
AC charger bulk charging current	750 mA (maximum)	From AC outlet	max. 35 hours*
Peak charging voltage	14.2 V (nominal)	From DC outlet	max. 4 hours*
Charge restart voltage	12.9 V (nominal)	*Maximum charging time occurs when battery is completely discharged.	
Float charge current ¹ mA (nominal)			
Charger input socket current	2.5 amps (maximum)		

General Specifications

Air compressor	250 psi (lbs. per square inch)
Jump-start cables	24" (61 cms), 4 AWG
Built-in incandescent light	5 watt (replaceable)
Operating/storage temperature	32°F - 104°F (0°C - 40°C) / 32°F - 86°F (0°C - 30°C)
Inverter low battery alarm	11.0 volts (nominal)
Inverter low battery shutdown	10.5 volts (nominal)
Dimensions (H x W x L)	9.5 x 8.1 x 15.8" (24.2 x 20.6 x 40.2 cm)
Weight	20 lb (9.0 kg)
Warranty	6 months
Part Number	852-1900

Note: Specifications subject to change without notice.

